

marantz®

SR6010

NETWORK A/V RECEIVER WITH WI-FI & BLUETOOTH



The new Marantz SR6010 is based on last year's highly successful SR6009 but offers several, significant improvements over its predecessor. Power remains the same with seven identical, high current, discrete amplifiers, each rated at 110 watts. With 9.1 channels of processing capability and 13.2 channel pre-outs, the SR6010 offer extreme versatility for the home theater enthusiast. Featuring both Dolby Atmos® and DTS:X™ (via future firmware update), users will be able to enjoy these new, more immersive surround sound formats that create a three-dimensional listening experience. With 8 HDMI inputs (including 1 conveniently located on the front panel) and 2 multi-zone/multi-source HDMI outputs, the SR6010 features an advanced video processing system. Prepared for the future, it is equipped to handle 4K Ultra HD full rate 60Hz content, 4:4:4 Pure Color sub-sampling, rec.2020 color gamut and 21:9 aspect ratio pass-through. It's also HDCP 2.2 compliant, which is a requirement for 4K Ultra HD copy-protected content. In addition, because we have upgraded the SR6010 to the Audyssey Platinum suite of technologies (MultEQ XT32, SubEQ HT and LFC), you get an even more accurate calibration of the system's speaker configuration to guarantee that every seat in the room is optimized. There is even an option for an Audyssey MultEQ Pro calibration. Like every new Marantz A/V receiver this year, the SR6010 has Wi-Fi B, G and N and Bluetooth® built in and supports Apple lossless (ALAC), gapless playback, FLAC HD 192/24 and even DSD and AIFF network streaming. Support for Spotify Connect® and Apple AirPlay® audio streaming are included as well. But we haven't changed everything. We have maintained its predecessor's well-deserved reputation for audio quality, a combination of effortless power, amazing detail, and sensual imaging, thanks to the use of current feedback technology and HDAM (Hyper Dynamic Amplifier Module) pre-amplification. And to get it all up and running quickly and easily, there's a handy Setup Assistant with its best-in-class on-screen graphic user interface.

us.marantz.com



PANDORA



Main Features

- Wi-Fi and Bluetooth built in
- Dolby Atmos and DTS:X (ready)
- 7ch discrete power amplifier, 110W per channel
- 13.2 ch preout with 9.2 ch processing
- Current Feedback topology with Marantz New HDAM
- Audyssey MultEQ XT32, LFC, Sub EQ HT, Pro ready, Audyssey Dynamic EQ and Volume
- Latest HDMI 2.0a with 4K 60Hz 4:4:4 resolution
- 7+1 HDMI in / 2 out (4K 60Hz, 3D, ARC, HDR, BT.2020)
- Full HDCP 2.2 support on all HDMI inputs and outputs
- HDMI scaling 1080p, 4k 50/60Hz
- MP3, WAV, AAC, WMA, AIFF
- HD Audio streaming: FLAC 192/24, DSD, ALAC
- Gapless Playback
- Spotify Connect, Pandora®, SiriusXM™, and Internet Radio support
- Phono (MM) input
- Setup Assistant and advanced GUI
- Big trapdoor design; Aluminum front panel
- Marantz Remote App for iOS and Android™ devices
- ECO mode
- 7.1 Channel Inputs and Zone 2 Preouts
- Gold Plated Inputs and Outputs Terminals
- ISF Certification
- C4 Certified IP Control
- Crestron Connected Certified

UPC

NA SR6010/U1B 6-99927-24075-2 Black

ca.marantz.com

because music matters



marantz®

SR6010

NETWORK A/V RECEIVER WITH WI-FI & BLUETOOTH



FEATURES	SR6010
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Surround	• / • / •
Dolby Atmos	•
DTS:X / DTS Neural:X	• (ready) / • (ready)
Multichannel Stereo	•
Compressed Audio Enhancer: MDAx2	•
NETWORK	
DLNA Certified	• (v1.5)
Lossy Formats MP3 / WMA / AAC	• / • / •
DSD Streaming	• (2.8 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay Audio Streaming	•
Windows PlayTo / Windows 8/RT Compatible	• / •
Internet Radio (vTuner) / Spotify Connect / Pandora / SiriusXM*	• / • / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna)
CONVENIENT AND SOUND	
FM / AM Tuner	• / •
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
High Grade Audio Components	•
Bluetooth	•
Auto speaker setup by microphone	Audyssey Mult EQ XT32 (Pro)
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video Conversion	CVBS > HDMI; Comp > HDMI
Video processing	>1080p, 4k 50/60Hz
ISF Certification	•
HDMI Pass-Through on Stand-By	•
3D video Pass-Through / Audio Return Channel	• / •
On Screen Display: Advanced GUI	•
GUI Overlay on HDMI	•
Setup Assistant (English, Spanish, French)	•
Smart Select	4 presets
Variable Cross Over	•
Multi-Room Zones	2
Optimized Bass Redirection	•

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3+1 / 1
Component In / Out	2 / 1
HDMI In / Out	7+1 / 2 (main + zone)
AUDIO	
Analog In / Out	5+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (13.2, 9.2 processing)
Subwoofer Out	2
Zone Audio Preout	•
7.1 Multichannel Input	•
OTHERS	
Gold-Plated Terminals	•
Speaker A / B	•
Height Speaker Terminal	•
Bi-Amp Drive	•
Multi-Room Speaker Terminal	Surround Back assignable
RS232 Control	•
IR Flasher In	•
DC Trigger Output	•
Marantz Remote Bus	•
Network: (IP-control / Update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
SPECIFICATIONS	
Number of Poweramps	7
Power Output Per Channel	
Maximum Power Output Per Channel	220 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	150 W
8 ohm, 20Hz - 20kHz, 0.08%, 2ch Drive	110 W
Audio Signal to Noise Ratio	100 dB
GENERAL	
Available Colors: Black	•
System Remote Control	RC025SR
Power Consumption in W	650
Power Consumption No-Sound (ECO ...on/off) in W	50 / 80
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in inches	17.3 x 15.7 x 6.3
Weight in lbs.	25.1

Design and specifications are subject to change by Marantz without notice.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/ third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

* This feature is not available in all countries.

* All specs can be subject to change.