

# marantz®

## SR5010

### NETWORK A/V RECEIVER WITH WI-FI & BLUETOOTH®



The SR5010 7.2ch Network A/V Receiver packs an unbelievable 100W of power per channel, to fill even large home theaters with Marantz sound. With Dolby Atmos® you'll experience revolutionary 3D surround sound, with the ability to create an overhead surround soundfield that dramatically expands the sonic space. And, via a firmware update (available late 2015), the SR5010 will be able to decode DTS:X™ soundtracks, which also deliver an immersive 3-dimensional soundspace no matter the number of speakers installed. In addition, it owns very high grade audio components that have been carefully selected. The whole internal circuit further enhances audio quality by delicately handling all signals via Marantz's own HDAMs (Hyper Dynamic Amplifier Module) in Current Feedback topology before passing them on to the power stage to fire up the connected speakers. Bluetooth and Wi-Fi are built in so you can enjoy your digital files wherever they are stored. It provides networking DLNA 1.5 facilities for audio streaming including DSD, FLAC HD & AIFF and Gapless, Internet radio, Spotify Connect® and AirPlay®. With 8 HDMI 2.0a inputs supporting HDCP 2.2 and 4K Ultra HD Full Rate with HDR and BT.2020 support, the SR5010 features an advanced video processing system with 4K upscaling. A second HDMI output to connect a projector and a TV at the same time, a 7.2 channel pre-out section and the RS232 connection makes the SR5010 very attractive even for custom installation purposes. The SR5010, is a true combination of style, power and ease.

#### Main Features

- Wi-Fi and Bluetooth built in
- Dolby Atmos and DTS:X (ready)
- 7ch discrete power amplifier, 100 W per channel
- Current Feedback topology and new Marantz HDAM
- Audyssey MultEQ XT auto speaker setup and room calibration
- Latest HDMI 2.0a version with 4K 60Hz 4:4:4 resolution
- 7+1 HDMI in / 2 out (4K 60Hz, 3D, ARC, HDR, BT.2020)
- Full HDCP 2.2 support on all inputs
- Advanced Video Processing with scaling of analog and digital signals up to 4K
- MP3, WAV, AAC, WMA, AIFF
- HD Audio streaming: FLAC 192/24, DSD, ALAC
- Gapless Playback
- Spotify Connect, Pandora®, SiriusXM™\*, Internet Radio support, AirPlay
- Setup Assistant and Advanced GUI
- Marantz AVR Remote App for iOS and Android™ devices
- ECO mode
- 7.1 channel Inputs, 7.2 Channel Preouts, and Zone 2 Preouts
- C4 Certified IP Control
- ISF Certification

#### UPC

NA SR5010/U1B 6-99927-28105-2 Black





## SR5010

### NETWORK A/V RECEIVER WITH WI-FI & BLUETOOTH



FEATURES	SR5010
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Multichannel Stereo	•
Compressed Audio Enhancer: MDAX2	•
<b>NETWORK</b>	
DLNA Certified	• (v1.5)
Lossy Formats MP3 / WMA / AAC	• / • / •
Lossless Formats FLAC / ALAC / WAV   AIFF	• / • / • / •
DSD Streaming	• (2.8MHz)
FLAC HD 192/24	•
WAV 192/24	•
ALAC 96/24	•
Gapless Playback	• (FLAC, WAV, ALAC, DSD)
AirPlay Audio Streaming	•
Windows PlayTo / Windows 8/RT Compatible	• / •
Internet Radio (vTuner)	•
Spotify Connect / Pandora / SiriusXM *	• / • / •
Compatible with Remote APP	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna)
<b>OTHERS</b>	
FM / AM Tuner	• / •
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
High Grade Audio Components	•
Bluetooth	•
Auto Speaker Setup by Microphone	Audyssey MultEQ XT
Audyssey Dynamic EQ / Dynamic Volume	• / •
HDMI Pass-Through on Stand-By	•
3D Video Pass-Through	•
Video Conversion	CVBS / HDMI; Comp / HDMI
Videoprocessing and -Scaling	1080p, 4k 30 / 25 / 24Hz
ISF Certification	•
Audio Return Channel	•
On Screen Display	Advanced GUI
GUI Overlay on HDMI	•
Setup Assistant (English, French, Spanish)	•
Smart Select	4 presets
Variable Cross Over	•
Optimized Bass Redirection	•

INPUTS/OUTPUTS	
<b>VIDEO</b>	
Composite In / Out	2+1 / 1
Component In / Out	2 / 1
HDMI In / Out	7+1 / 2
<b>AUDIO</b>	
Analog In / Out	4+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (7.2)
Zone Audio Preout	•
Subwoofer Out	2
<b>OTHER</b>	
7.1 Multichannel Input	•
Speaker A / B	•
Height Speaker Terminal	Surround Back Assignable
Bi-Amp Drive (5.1 ch Setting)	•
Multi-Room Speaker Terminal	Surround Back Assignable
RS232 Control / Web Control	• / •
IR Flasher In	•
Marantz Remote Bus	•
Network: (IP-Control / Update)	• / •
Front Inputs: Audio / Composite / HDMI / USB	• / • / • / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
<b>SPECIFICATIONS</b>	
Number of Poweramps	7
<b>Power Output Per Channel</b>	
Maximum Power Output Per Channel	200 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	140 W
8 ohm, 20Hz - 20kHz, 0.08%, 2ch Drive	100 W
Audio Signal to Noise Ratio	100 dB
<b>GENERAL</b>	
Available colors: Black	•
System Remote Control	RC024SR
Power Consumption in W	650
Power Consumption No-Sound (ECO ...On/Off) in W	45 / 75
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in inches	17.3 x 6.3 x 13.6
Weight in lbs.	22.1

Design and specifications are subject to change by Marantz without notice.