

marantz®

SR7010

NETWORK A/V RECEIVER WITH WI-FI & BLUETOOTH



Our new top-of-the-line SR7010 marks the epitome of power, connectivity and versatility. Not only does it perfectly and expertly handle any kind of high resolution multichannel audio format, but it also offers an extended network package including audio streaming, internet radio, Spotify Connect® and Apple AirPlay®, and built-in Wi-Fi and Bluetooth® capabilities. Superb surround sound audio quality from all formats is guaranteed by the powerful Analog Devices 32-Bit SHARC DSPs. Immersive surround sound decoding technologies include both Dolby Atmos and DTS:X (via future firmware upgrade), with the option for Auro-3D via a paid upgrade. In addition, the SR7010 further enhances audio quality by delicately handling all signals by employing an all-discrete, Marantz-exclusive HDAM preamp stage, before passing them along to the nine high-quality amplifier channels, each with 125 watts of high current output. For maximum versatility, the SR7010 can process up to 11 channels to take full advantage of all three immersive audio formats. It also offers equally high levels of video performance by way of its eight HDMI 4k/60Hz pass through and scaling inputs. Video output flexibility includes two HDMI monitor outputs and a third, multi-zone/multi-source HDMI output. All HDMI inputs and outputs support both HDCP 2.2 copy protection and HDMI 2.0a for 4K UHD content, as well as uncompressed 4:4:4 color subsampling and rec.2020 color gamut. There is even a moving magnet phono input. Setup, calibration and operation are achieved quickly and easily via Audyssey MultEQ XT32 auto-calibration and advanced on-screen graphic user interface. The built-in AM/FM tuner features HD radio for superior sound quality.

Main Features

- Wi-Fi and Bluetooth built in
- Dolby Atmos and DTS:X (ready)
- Auro-3D upgradeable (optional paid upgrade)
- 9ch discrete power amplifier, 125W per channel
- 13.2 ch preout with 11.2 ch processing
- Current Feedback topology with Marantz New HDAM
- Audyssey MultEQ XT32, LFC, Sub EQ HT, Pro ready, Audyssey Dynamic EQ and Volume
- Latest HDMI 2.0a with 4K 60Hz 4:4:4 resolution
- High quality 192kHz / 32bit DAC
- 7+1 HDMI in / 3 out (4K 60Hz, 3D, ARC, HDR, BT.2020)
- Full HDCP 2.2 support on all HDMI inputs and outputs
- HDMI scaling 1080p, 4k 50/60Hz
- MP3, WAV, AAC, WMA, AIFF
- HD Audio streaming: FLAC 192/24, DSD, ALAC
- Gapless Playback
- Spotify Connect, Pandora®, SiriusXM™, and Internet Radio support
- Phono (MM) input
- Setup Assistant and advanced GUI
- Big trapdoor design; Aluminum front panel
- Marantz Remote App for iOS and Android devices
- ECO mode
- HD Radio Built In
- 7.1 Channel Inputs, Zone 2 and Zone 3 Preouts
- Gold Plated Inputs and Outputs Terminals
- ISF Certification
- C4 Certified IP Control
- Crestron Connected Certified



because music matters



marantz®

SR7010

NETWORK A/V RECEIVER WITH WI-FI & BLUETOOTH



FEATURES	SR7010
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Surround	• / • / •
Dolby Atmos	•
DTS:X / DTS Neural:X	• (ready) / • (ready)
Multichannel Stereo	•
Compressed Audio Enhancer: MDAx2	•
NETWORK	
DLNA Certified	• (v1.5)
Lossy Formats MP3 / WMA / AAC	• / • / •
DSD Streaming	• (2.8 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless Playback	• (FLAC, WAV, ALAC, DSD)
AirPlay Audio Streaming	•
Windows PlayTo / Windows 8/RT Compatible	• / •
Internet Radio (vTuner) / Spotify Connect/ Pandora/ SiriusXM*	• / • / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna)
CONVENIENT AND SOUND	
FM / AM Tuner / HD Radio	• / • / •
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
High grade Audio Components	•
Bluetooth	•
Auto Speaker Setup by Microphone	Audyssey Mult EQ XT32 (Pro)
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video Conversion	CVBS > HDMI; Comp > HDMI
Video processing	>1080p, 4k 50/60Hz
ISF Certification	•
HDMI Pass-Through on Stand-By	•
3D Video Pass-Through / Audio Return Channel	• / •
On Screen Display: Advanced GUI	•
GUI Overlay on HDMI	•
Setup Assistant (English, Spanish, French)	•
Smart Select	4 presets
Variable cross over	•
Multi-Room zones	3
Optimized Bass Redirection	•

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3+1 / 2
Component In / Out	3 / 1
HDMI In / Out	7+1 / 3 (main + zone)
AUDIO	
Analog In / Out	5+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (13.2, 11.2 processing)
Subwoofer Out	2
Zone Audio Preout	•
7.1 Multichannel Input	•
OTHERS	
Gold-Plated Terminals	•
Speaker A / B	•
Height Speaker Terminal	•
Bi-Amp Drive	•
Multi-Room Speaker Terminal	Surround Back assignable
RS232 Control	•
IR Flasher In	•
DC Trigger Output	•
Marantz Remote Bus	•
Network: (IP-Control / Update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
SPECIFICATIONS	
Number of Poweramps	9
Power Output Per Channel	
Maximum Power Output Per Channel	235 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	165 W
8 ohm, 20Hz - 20kHz, 0.05%, 2ch Drive	125 W
Audio Signal to Noise Ratio	100 dB
GENERAL	
Available colors	Black
System Remote Control	RC026SR
Power Consumption in W	710
Power Consumption No-Sound (ECO on/off) in W	65 / 110
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in inches	17.3 x 16.2 x 7.3
Weight in lbs.	30.4

Design and specifications are subject to change by Marantz without notice.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/ third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

* This feature is not available in all countries.

* All specs can be subject to change.